



**LoRa ID**  
Ref. IDF320002



**The industrial LoRa tag to identify your assets on long range distance**

- Compatibility with public **LoRaWAN** network or **private LoRa network**
- **Integrated motion sensor**
- Battery life cycle: up to **16 years**
- Sturdy industrial casing – **IP68 waterproof**
- Integrated **NFC** chip

**SPÉCIFICATIONS TECHNIQUES**

<b>Voltage supply</b>	3.6 VDC – 2 LS14500 lithium battery replaceable by the user
<b>Frequency</b>	868MHz
<b>Operating mode</b>	<ul style="list-style-type: none"> <li>• «Periodic wake-up» mode: Periodic data transmission on LORA network on a customizable frequency</li> <li>• «Acquisition» mode: data transmission based on changes in magnetic sensors state</li> </ul> Downlink: change in LoRa class (A, C)
<b>Transmission power</b>	From 4 to 14 dBm (adjustable value)
<b>Transmission period</b>	60 seconds to 24 hours (adjustable value)
<b>Battery life cycle</b>	<b>16 years:</b> one transmission a day at +14dBm <b>15 years:</b> one transmission every 6 hours at +14dBm
<b>Sensors</b>	<ul style="list-style-type: none"> <li>• <u>Measurement range:</u> <ul style="list-style-type: none"> <li>- MAG: 2cm</li> <li>- MOV: motion counter up to 32768 thresholds overrun (AccThresh).</li> </ul> </li> <li>• <u>Resolution:</u> <ul style="list-style-type: none"> <li>- MAG: state change counter on 15MSB (non-signed). Current state in the LSB.</li> <li>- MOV: threshold overrun counter on 15MSB (non-signed). Current state in the LSB.</li> </ul> </li> <li>• PICK TO LIGHT function (High luminosity LED)</li> </ul>
<b>Radio frame format</b>	25 bytes frame format, with identification frame (5 bytes), magnetic sensor state (2 bytes), motion sensor state (3 bytes)
<b>Configuration</b>	Interface/Protocol: NFC (type 2) - Device Manager Software
<b>Operating temperature</b>	-40°C to +85°C
<b>Casing</b>	<ul style="list-style-type: none"> <li>• 119 x 24,5 x 51 mm</li> <li>• 2 fixation holes: øM4</li> <li>• waterproofness IP 68</li> <li>• DELRIN (POM C) Compatible with agri-food products (90/128/EEC)</li> </ul>
<b>Norms</b>	RADIO: EN 300 220-2 / EN 300 220-1 CEM: EN 301 489-3 / EN 301 489-1 Electrical security: EN 60950-1 Health: EN 62311

DISTRIBUTED BY TEXIM EUROPE

## The Netherlands



Elektrostraat 17  
NL-7483 PG Haaksbergen

T: +31 (0)53 573 33 33  
F: +31 (0)53 573 33 30  
E: [nl@texim-europe.com](mailto:nl@texim-europe.com)

## Belgium



Zuiderlaan 14 bus 10  
B-1731 Zellik

T: +32 (0)2 462 01 00  
F: +32 (0)2 462 01 25  
E: [belgium@texim-europe.com](mailto:belgium@texim-europe.com)

## UK & Ireland



St. Mary's House, Church Lane  
Carlton Le Moorland  
Lincoln LN5 9HS

T: +44 (0)1522 789 555  
F: +44 (0)845 299 22 26  
E: [uk@texim-europe.com](mailto:uk@texim-europe.com)

## Germany North



Bahnhofstrasse 92  
D-25451 Quickborn

T: +49 (0)4106 627 07-0  
F: +49 (0)4106 627 07-20  
E: [germany@texim-europe.com](mailto:germany@texim-europe.com)

## Germany South



Martin-Kollar-Strasse 9  
D-81829 München

T: +49 (0)89 436 086-0  
F: +49 (0)89 436 086-19  
E: [germany@texim-europe.com](mailto:germany@texim-europe.com)

## Austria



Warwitzstrasse 9  
A-5020 Salzburg

T: +43 (0)662 216 026  
F: +43 (0)662 216 026-66  
E: [austria@texim-europe.com](mailto:austria@texim-europe.com)

## Nordic region



Sdr. Jagtvej 12  
DK-2970 Hørsholm

T: +45 88 20 26 30  
F: +45 88 20 26 39  
E: [nordic@texim-europe.com](mailto:nordic@texim-europe.com)

## Italy



Via Matteotti 43  
IT-20864 Agrate Brianza (MB)

T: +39 (0)39 971 3293  
F: +39 (0)39 971 3293  
E: [italy@texim-europe.com](mailto:italy@texim-europe.com)

## General information



[info@texim-europe.com](mailto:info@texim-europe.com)  
[www.texim-europe.com](http://www.texim-europe.com)